

Barcode-reader

# SUNMI Blink



Plug and play support for personalized customization  
Comes with sensor lights beeps for prompt payment  
Ergonomic scan code payment angle



Metal texture frame



Mobile payment

## SUNMI BLINK

Technical specifications



**OS**  
Windows  
iOS  
Android  
Linux



**Scanning Window**  
75\*75mm



**Recognition Precision**  
QR code > 10mil



**Sensor**  
0.3 MP  
CMOS sensor



**Operating Current**  
< 190mA



**Symbologies**  
QR CODE  
CODE 128(1D code)



**Maximum Frame Number**  
30FPS



**Input**  
5V ± 0.5V



**Size**  
97\*90\*100mm



**Port**  
1x USB Type-A  
(with 1.5m wire)



**Operating environment**  
Operating temperature: 0°C ~ 40°C  
Storage temperature: -10°C ~ 50°C  
Operating humidity: 5% ~ 95% (no condensation)

Note:

1. Actual product specifications when sold take precedence over what may be listed at this catalogue; Any changes may be made without prior notification